

Product information:

The TRV106 transformer designed for use with the VIRO5(D). This transformer can be used for converting VIRO5 speakers allowing them to be fitted in 70/100V installations where long cable runs can be used.



System specifications:

| | | |
|---------------------------|-------------------|---------------------------------------|
| Line Transformer Tappings | 1 | 83 Ω - 100 V / Not used - 70 V / 60 W |
| | 2 | 167 Ω - 100 V / 60 W - 70 V / 30 W |
| | 3 | 333 Ω - 100 V / 30 W - 70 V / 15 W |
| Impedance | | 8 Ω |
| | | 16 Ω |
| Connection | | SnapConnect™ |
| | | Stripped & tinned wires |
| Frequency | Response (± 3 dB) | 50 Hz - 20 kHz |

Product Features:

| | |
|--------------|-------------------------------|
| Weight | 3.086 lb |
| Construction | Copper |
| Accessories | Included |
| | Mounting bolt, nut and washer |